

03057 Slim Digital Multimeter with Temperature Tester



- Auto-range
- LCD with Max. reading of 3999, with high definition white backlight
- Used to measure DC/AC voltage, DC/AC current, resistance, capacitance, continuity test, diode, frequency, duty cycle, temperature
- Ultra-thin, easy to hold

No.			
03057	-	12	6.5

▲ Warranty of 2 years (excluding fuse, battery and probe).

Function	03057 Slim Multimeter with Temperature Test
Maximum Reading	3999
Automatic/manual range	Automatic
DC Voltage	400mV/4V/40V/400V/600V
AC Voltage	400mV/4V/40V/400V/600V
DC Current	400μA/4000μA/40mA/400mA/4A/10A
AC Current	400μA/4000μA/40mA/400mA/4A/10A
Resistance	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ
Capacitance	10nF/100nF/1μF/10μF/100μF
Frequency	10Hz/100Hz/1KHz/10KHz/100KHz
Duty ratio	5%-95%
Temperature	-20°C~1000°C (4°F~1832°F)
Short-circuit beep	Yes
Diode test	Yes
Data Retention	Yes
Backlight	White
Auto shutdown	Yes
Common	
Power	Two 1.5 V AAA batteries
Size	175×78×18.5mm
Weight	190G (battery included)

03031A Infrared Thermometer



- Non-contact temperature thermometer
- Three-color backlight display
- The temperature change point can be quickly detected according to the settings.
- Distance coefficient ratio is 12:1

No.			
03031A	1	12	5

▲ Warranty of 2 years (excluding battery).

Performance	
Measuring Range	-38°C ~ +520°C (-36.4 °F ~ +968 °F)
Spectral Response	7.5 ~ 13.5μm
Measurement accuracy	+/-2 °C (4° F) or 2% of the reading, taking the one with bigger error range
Response time	1s, 95%
Distance coefficient ratio D:S	12 : 1
Emissivity	0.95
Reading Resolution	0.1°C / 0.1 °F
Backlight automatic shutdown time	15s
Automatic shutdown time	60s
Operating temperature	0°C ~ 40°C
Operating humidity	<75%
Battery	Two 1.5 V AAA batteries
Size (mm)	160 X 118 X 40
Weight (G)	155g (battery included)